Storm Games

Street Casino 2016 Storm HD User Guide



The following pages provide detailed instructions of how to use either Storms Back Office Systems.

Gaining Access to the Back Office Menu (Engineers Menu)

To gain access to the Back Office / Engineers Menu, **SIMPLY OPEN THE TOP DOOR OF THE KIOSK** and the following screen will appear.

General	Collect	Engineers	Setup	Site Name	Receipt Audit Log	Config	Menu	Detailed Stats
SITE	: SL	.003 D	ays	Left: 5	003	RE	ILL 00	0000000
Tuesday Last Ga	Please I 3 me	Please	Enter Yo	ur Password:				
		Passwo	ord		-			
Last Pa DATE : DATE : DATE : DATE : DATE :	yn 26 26 26 26 25		1 4 7	2 3 5 6 8 9		achine Vol	ume)
Pre	SS	Ok	_	Cancel	re ali Sc	ess to brate reen	Press	s for Next Page

On the keyboard on the screen insert the following password to gain access to the full Engineers Menu. **000071 then Ok**

General Page



This screen allows the Site Manager or Engineer to view the Last Game Plays and also lower down the page it displays the last payments that have been.

There are three other functions that can be used on this page.

Firstly, you can alter the volume level by sliding your finger up & down the **Master Machine** Volume Slide

Secondly, you can recalibrate the Touch Screen if the screen is slightly out by simply pressing the **Press to Calibrate Screen** Icon. Once this button is fired you are required to touch the four targets to complete the calibration routine.

Collect Page

General	Collect	Engineers	Setup	Site Name	Receipt Audit Log	Config	Menu	Detailed Stats		
Back Office Cash Collection										
Meter	rs			nformation						
RE	FILL OC	0000000		£1 Hopper C	Controls	- 10p Ho	opper Co	ontrols		
CASH CASH	H In 00	0000000		Float Hopper £ to Max		Floa 10p	t Hopper to Max	r + 5		
CHAI		0000000		Hopper £1 Lev	el Hopper MAX Level	Норр	er 10p Leve	Hopper MAX Leve		
NOTES	S In 00	0000000		000000	900	000	0000	200		
NOTES	Out 00	0000000		Dump 35 Coins	- 5	Du	mp 10p opper	- 5		
		0000000								
HAND	PAY 00	0000000		Dump Balance	2					
				Note Recyc	ler					
Press To EXIT				Send All Notes to Stacker	Notes in Recycler	Press for Next Page				
				Feed Notes into the	Notereader to Top Up the Recy	cler				

The Collect screen enables you to see the Short Term Cash In / Out meters so you can calculate how the machine is performing and this screen assists the collector to set the hopper level and also dump the hopper content.

This screen also has several other functions to assist the Engineer / Collector.

Hopper Max Level – The hopper level is normally set to £900 once its leaves our factory, but by using the **ADD 5** and the **DEDUCT 5 icons** you are able to change the hopper level to the required level.

Float Hopper to Max – By pressing this icon, this sets the actual hopper level to what has been set in the **Hopper Max Level.**

Dump 350 Coins – This dumps the hopper content up to £350

Dump Balance of Coins – This dumps any excess coins in the hopper.

Send All Notes to Stacker – This show the Engineer / Collector how many notes are currently in the Note Recycler unit and by pressing this icon it gives the facility to empty the content of the recycler unit into the note stacker below.

Engineers Page

General	Collect	Engineers	Setup	Site Name	Receipt	Audit Log	Config	Detailed	Stats	
Bac	k Off	lice				Eng	inee	ers		
Periphe	erals Attac	hed	Ha	irdware Ever	nts		-No	ote Recycle	r —	
NOTER	READER	OK 🗆	BU	JTTONUP 7]			Send All		es in Recycler
HOPPE	ECH OK		N	ote Reader	Enable	Disable		Notes to Stacker	Notes to Stacker	
				Coin Mech	Enable	Disable				
				Coin Route	Cashbox	Hopper	Норр	per Pay£	1	DUMP
Mac1	Network 00000008	Available] Realtek F	Cle GBE	E Family Co		MAC	ENABLE	DHCP		
Mac2	00000010] Realtek F	Cle GBE	E Family Co	ENABLE	DHCP				
	IP Add	iress		Subnet	G	iteway		DNS		
IP1 1	27.0.0.1									SETIP
IP2										SETIP
		VENU	E ASSET	NUMBER	1		SAVE			
USE T	ro ^{REG}	SISTER MACH TITO NETWO	INE ON RK	CLEAR TIT	O Settings		ZER	O CREDIT	on Ma	achine
Pres	ss To EXI	C KE	nscreen YBOARD	Lamp Co Lamp1	ontrols	Lamp3	Lamp	4 Pr	ess fo Pag	r Next le
				Lamp5	Lamp6	Lamp7	Lamp	<u> </u>		

The Engineers Page is to assist the engineers if there is a fault on the machine

Peripherals Attached – This allows the engineer to see if the CC Talk line is working ok and if the Coin Mech, Hopper & Note Accepter is visible and working.

Zero Credit – Allows the engineer to reset the credits back to Zero

Send all Notes to Stacker – If the machine has a NV11 fitted, it normally will send one of the note denominations to the recycler unit. This allows you to empty the recycler unit into the stacker at the bottom of the Note Accepter.

Lamp Controls – Lets the engineer fire each individual lamp on the buttons.

Hardware Events – Once a button is pressed or a coin or note inserted it will appear here.

Coin Route – Allows engineer to divert the £1 either into the hopper or cash box

Hopper – If fitted, the engineer can either pay 1 x £1 coin at a time or dump the hopper content.

Set Up Page

General	Collect	Engineers	Setup	Site Name	Receipt Audit	t Log	Config	Detailed St	ats
Bac	k Of	fice			S	et	up		
Machi	ne Categ	ory		Broad	and and EDC				
700/	CAT C CAT B4				Machine is connected to roadband				
/6%	0470	90%					IECTED CO M3		
Recei PRII	pt Printer NTER is (DFF	e Receipt for its only OVEF (pence)	Han 10	dpay And Note 00 DEC se Handpay Ov	Recy 	cler Denom I 10 Recycl	Change er NOTE De	ENABLED
Pri	ess To E	кIT						Press Pa	for Next age

Category Of Machine – Enables the customer to change between what percentage settings they require & Machine Category. If you wish to change category, you require a password which is **STORM**

Printer – If a printer is fitted this allows you to turn the printer off/ on, but the Engineer will need to press the **Save Receipt Printer Setting icon** to confirm the printer is enabled or disabled and by pressing the **INC & DEC Icons** this allows you to choose what printer payout level the customer requires.

Venue Name Page



This allows the engineer to input the site name on ticket payout kiosks.

Receipt Audit Log Page

General	Collect	Engineers	Setup	Site Name	Recei	ipt Audit Log	Config	Menu	Detailed Stats
Bac	k Of	fice			F	leceip	t Auc	lit I	og
DATE	: 16/06/ : 16/06/	2015 PAYO 2015 PAYO	CODE:	008L AMO	JNT : : UNT :	£64.00 £100.00			^
DATE	: 16/06/	2015 PAYO	ODE:	YOSC AMO	UNT :	£60.00			
DATE	: 16/06/	2015 PAYO	ODE:	68W0 AMO	UNT :	£80.00			-
DATE	: 17/06/	2015 PAYO 2015 PAYO	CODE:	6KNK AMO	UNT :	£64.00			
DATE	: 17/06/ : 17/06/	2015 PAYO 2015 PAYO	CODE:	GA1C AMO B8GM AMC	UNT : UNT :	£80.00 £84.00			
DATE	: 22/06/ : 22/06/	2015 PAYO 2015 PAYO	CODE:	QDTI AMOL GJ7O AMO	JNT : I UNT :	£47.00 £1.00			
DATE	: 22/06/	2015 PAYO 2015 PAYO	CODE:	3PJU AMOI JU52 AMOI	JNT : : JNT : :	£6.00 £4.00			
DATE	: 22/06/	2015 PAYO	CODE:	1J63 AMOU	INT : £	2.00			~
				Clear D	own	Print Off			
				Receip	ots	Receipt Au	dit	Pr	ess for Next
Pr	ess To E	хіт							Page

The Receipt Audit Log allows the collector or engineer to verify the tickets that have been paid out

Clear Down Receipts – Allows you to clear the tickets that have been paid out and verified.

Print Off Receipt Audit - This gives two copies of the cash out receipt and also a breakdown of each cash in / out of each lottery stake.

Kiosk ID Number



This enables the machine supplier to enter in the serial number of the kiosk, but rarely used.

Detailed Game Stats

General	Collect	Engineers	Setup	Site Name	Receip	ot Audit Log	Config	Menu	Detailed Sta	ats
Deta	ailed	Game	sta	its	Sho	wing S	Summa	ary T	otals	
G	ame Nam	ne Total P	Plays	Total Stake	Tota	al Won	Total Prof	iit Pa	у%	
PL	AYS :	STA	KED :	WC	DN :	P	ROFIT:		%	6
	Totals	Stake	Be	tween f	From:	30 Ju	ine 2	2015 -		
	lotais	Breakdown	D	ates	Го:	30 Ju	ine 2	2015 -		
Pr	ess To E)	хіт						Pro	Page	

The Detailed Stats page gives an in depth view of the stats screen.

Total Button – Gives you a total overview of how the machine is performing. As pictured below, this screen provides a view of the games that have been played, total stake per game, the amount won and the total profit across all stakes.

Showing Stake Breakdown Button

General	Collect	Engineers	Setup	Site Name	Recei	pt Audit Lo	g Config	Menu	Detailed Stats
Det	ailed	Game	Sta	its	Shc	wing	Summ	ary T	otals
G	ame Nan	ne Total F	Plays	Total Stake	To	tal Won	Total Prot	fit Pa	y%
							_		
PL	AYS :	STA	KED :	W	: NC		PROFIT:		%
	Totals	Stake	Be	tween	From:	30 J	une 2	2015	
	rotuio	Breakdown	D	ates	То:	30 J	une 2	2015 -	
Pr	ess To EX	KIT						Pre	ess for Next Page

Stake Breakdown - This lists what game has been played on each of the different stakes and what the profit has been made on that stake per game.

Between Dates Button

General	Collect	Engineers	Setup	Site Name	Rece	ipt Audit Lo	og Config	Menu	Detailed Stats
Det	ailed	Game	e Sta	its	Sho	owing	Summ	ary T	otals
G	ame Nan	ne Total I	Plays	Total Stake	e To	tal Won	Total Prot	fit Pa	y%
В	AVS	CTA							
					-	30		2015	%
· ·	Totals	Stake Breakdown	Be	tween ates	From: To:	30 J	une 2	2015	
Pr	ess To E	хіт						Pre	ess for Next Page

Between Two Dates – This allows the Engineer / Site to see how the machine has performed over a certain amount of time.

FOR ANY TECHNICAL QUERIES PLEASE CALL STORM GAMES ON 01902 374124